

Doc. No.	KP1/10A.2B/3/3/01
ISSUE NO.	2
REVISION NO.	3
Date of Issue	2016-06-16
Page 1 of 28	

	NAME	DESIGNATION	SIGNATURE	DATE
Prepared by:	Margaret Kanini	Chief Engineer, DSM & Metering Solutions	Julie	बंध:वाः
Checked by:	Rosemary Oduor	Manager, Energy Management	alph	116
Approved by:	Joshua Mutua	General Manager, Customer Service	Bedie	28/11



Doc. No.	KP1/10A.2B/3/3/01
ISSUE NO.	2
REVISION NO.	3
Date of Issue	2016-06-16
Page 2 of 29	

Using PLC as medium of communication between MCU and UIU

Page 2 of 28

TABLE OF CONTENTS

- 0.1 Circulation List
- 0.2 Amendment Record

FOREWORD

INTRODUCTION

- 1. SCOPE
- 2. NORMATIVE REFERENCES
- 3. TERMS AND DEFINITIONS
- 4. REQUIREMENTS
- 5. INFORMATION AND WARRANTY
- 6. ANNEXES

ANNEX A: TECHNICAL PARTICULARS

ANNEX B: GUARANTEED TECHNICAL PARTICULARS

Meri



Using PLC as medium of		
communication between MCU		
and UIU		

Doc. No.	KP1/10A.2B/3/3/01	
ISSUE NO.	2	
REVISION NO.	3	
Date of Issue	2016-06-16	
Page 3 of 28	<u> </u>	

0.1 Circulation List

Сору №.	Copy Holder	
1	GM, SUPPLY CHAIN	
2	MANAGER, STANDARDS DEVELOPMENT	

Electronic copy (pdf) on KPLC Server currently: http://172.16.1.40/dms/browse.php?fFolderId=23

0.2 Amendment Record

Rev No.	Date (YYYY-MM-DD)	Description of Change	Prepared by (Name & Signature)	Approved by (Name & Signature)
3	2015-04-25	Amendments on clauses- 4.2.1.4, 4.2.1.6, 4.2.1.9, 4.2.2.1.2, 4.2.2.1.10, 4.2.2.2.11,4.3.2, 4.3.3, 4.5.2 (d),4.5.9, 5.10, 5.4 (a), 5.7 & 5.8		
4	2016-04-18	Amendment on Clauses 4.2.2.1.12		
5	2016-06-17	Amendment on Clauses 4.2.1.4, 4.2.1.20, 4.2.1.21, 4.2.2.1.7, 4.3.1, 4.3.2, 4.3.3,4.5.11; Inclusion: clauses 4.2.1.2.10, 4.2.2.2.20		
6	2016-07-25	Amendment on Clauses 4.1.1, 4.1.2, 4.2.1.5, 4.2.1.6, 4.2.1.11, 4.2.1.19, 4.2.1.27, 4.5.2		2
		Inclusion 4.2.1.4, 4.2.1.22, 4.2.1.23, 4.2.1.24, 4.2.1.25, 4.2.1.26	2	





Doc. No.	KP1/10A.2B/3/3/01
ISSUE NO.	2
REVISION NO.	3
Date of Issue	2016-06-16
Page 4 of 28	

Using PLC as medium of communication between MCU and UIU

FOREWORD

This specification lays down requirements for single-phase DIN rail mounting split prepayment meters for active energy, where the communication between MCU and UIU is by means of PLC. The specification is intended for procurement of equipment and does not include provision of contract.

The specification was prepared to establish and promote uniform requirements for singlephase split prepayment meters for active energy to be used at Kenya Power and Lighting Company Ltd. The specification lays down the minimum requirements for equipment acceptable for use in the KPLC system.





Doc. No.	KP1/10A.2B/3/3/01
ISSUE NO.	2
REVISION NO.	3
Date of Issue	2016-06-16
Page 5 of 28	

Using PLC as medium of communication between MCU and UIU

1. SCOPE

This specification applies to newly manufactured, single-phase Din rail mounting static watthour prepayment meters for direct connection, for measurement of alternating current electrical energy consumption at a nominal frequency of 50 Hz.

The method of credit transfer shall be through encrypted numeric tokens complying with the 20-digit STS encryption algorithms. The meters shall include a load switch for the purpose of interruption or restoration of the electricity supply to the load in accordance with the current value of the available credit maintained in the prepayment meter.

The Measurement and Control Unit (MCU) shall be separated from the User Interface Unit (UIU) and method of communication between them shall be over Power Line Carrier for a distance not less than one hundred (100) metres.

2. NORMATIVE REFERENCES

The following documents were referred to during the preparation of this specification; in case of conflict, the requirements of this specification take precedence.

- [1] IEC 60529: Degrees of protection provided by Enclosures (IP Code)
- [2] IEC 62055-31:2005 Electricity metering Payment systems Part 31: Particular requirements Static payment meters for active energy (classes 1 and 2).
- [3] IEC 62052-11:2003, Electricity Metering equipment (a.c) General Requirements, Tests and Test Conditions- PART 11: Metering equipment.
- [4] IEC 62053-21:2003, Electricity metering equipment (a.c) Particular Requirements Part 21: Static meters for active energy (Class 1.0).
- [5] SANS1524-1:2004 Electricity prepayment Systems, Part 1: Prepayment meters.

3. TERMS AND DEFINITIONS

The definitions given in 2 shall apply.

KPLC: Kenya Power & Lighting Company Limited

MCU: Measurement and Control Unit





Doc. No.	KP1/10A.2B/3/3/01
ISSUE NO.	2
REVISION NO.	3
Date of Issue	2016-06-16
Page 6 of 28	

Using PLC as medium of communication between MCU and UIU

OFDM: Orthogonal Frequency Division Multiplex

PLC: Power Line Carrier

UIU: User Interface Unit

SRE: Significant Reverse Energy

4. REQUIREMENTS

Prepayment meters shall comply with the requirements of 2.1 and 2.3 for outdoor meters. The prepayment meters shall be mounted as for normal service.

4.1 Operating conditions requirements

- **4.1.1** The meters shall be suitable for operation in tropical climate where temperatures may vary from -1 to +60° Celsius.
- **4.1.2** Average Annual Relative humidity up to 90% and altitude of up to 2,600m.
- **4.1.3** The meters shall be used for measurement of active energy for domestic loads under tropical climate conditions.

4.2 Design and construction requirements

4.2.1 General

- 4.2.1.1 The requirements given in 2.1 shall apply.
- 4.2.1.2 The Measurement and Control Unit (MCU) shall be of DIN rail mounting with locking clip, to fit to a 35 mm Din rail.
- 4.2.1.3 The MCU and UIU shall communicate via PLC for a distance of not less than one hundred (100) meters.
- 4.2.1.4 The meters shall be constructed as 1 phase 2-wire meters.
- 4.2.1.5 The meters shall have terminals as follows: The Connection to the meter shall be Bottom-In, Bottom-Out with Live in and Neutral in terminals at the base level to allow





Doc. No.	KP1/10A.2B/3/3/01
ISSUE NO.	2
REVISION NO.	3
Date of Issue	2016-06-16
Page 7 of 28	

Using PLC as medium of communication between MCU and UIU

racking of the meter on a test bench. The meter terminals shall have a protection cover against ingress of water.

- 4.2.1.6 The MCU dimensions shall not exceed: Height = 170 mm; Width = 60 mm; and Depth = 95 mm; and meter base shall be on the width side where the Din rail is mounted.
- 4.2.1.7 The MCU body shall be ultrasonically sealed for life and there should be no screws on the MCU body except for the termination of cables.
- 4.2.1.8 The meter shall have terminal cover open detection. Once the terminal cover is opened, the load shall be disconnected.
 - (a) The MCU shall be supplied with loading switch in open mode and installer can open terminal cover when MCU is not activated by commissioning code (token).
 - (b) After installation of MCU, the installer will input a commission code (token) to close the loading switch and activate terminal cover open detection function.
 - (c) After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes.



Doc. No.	KP1/10A.2B/3/3/01
ISSUE NO.	2
REVISION NO.	3
Date of Issue	2016-06-16
Page 8 of 28	

- 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes.
- 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance.
- 4.2.1.11 Terminal holes shall be of at least 10mm diameter and 15mm in depth. The dimension from the terminal holes to meter base shall not exceed 20mm.
- 4.2.1.12 The meter's terminal screw inserts shall be sealable with utility wire seals.
- 4.2.1.13 The meters protection class shall be class II (Double insulated).
- 4.2.1.14 The meters shall have a non-volatile memory capable of data storage and with longterm data retention period of not less than 10 years or for the certified life of the meter or whichever is greater without an electrical supply being supplied to the meter.
- 4.2.1.15 The meters shall have register codes to indicate information like instantaneous power, current credit register, power fail counter, last credit token number, value of last credit token, etc. The values shall be available on the UIU display.
- 4.2.1.16 The principal unit for the measured values shall be the kilowatt-hour (kWh).
- 4.2.1.17 The meter shall have a means of reading the credit register to within a resolution of at least 0.01 kWh for testing purposes.
- 4.2.1.18 The meters shall detect significant reverse energy (SRE) when the line and load wires are swapped.
- 4.2.1.19 The meters shall continue to operate correctly and decrement credit during SRE detection.
- 4.2.1.20 The meters shall have LED indicators for testing and indication of kWh consumption.
- 4.2.1.21 The meters shall have an optical communication port, compliant to IEC 62056-21 for accessing information stored inside the meter through a hand held unit.
- 4.2.1.22 The meters shall support two-way communication.
- 4.2.1.23 The meters shall be compliant with the DLMS/COSEM or equivalent communication protocol.
- 4.2.1.24 The meters shall have PLC communication module for communication to data concentrators for a distance of over 1,000 meters.
- 4.2.1.25 The meters shall work under postpaid mode or prepaid mode. The switch of mode shall be done via meter specific token or optical communication.



Doc. No.	KP1/10A.2B/3/3/01
ISSUE NO.	2
REVISION NO.	3
Date of Issue	2016-06-16
Page 9 of 28	

- 4.2.1.26 The meters shall be supplied together with three copies of software for interrogating the meter data; and it shall not be possible to reprogram the meters using this software.
- 4.2.1.27 The MCU shall conform to the degree of protection IP 54 as given in IEC 60529. The terminals shall be so designed so as to ensure protection from ingress of water and dust.
- 4.2.2 Functionality
- 4.2.2.1 Measurement and Control Unit (MCU)
- 4.2.2.1.1 The MCU shall have a load switch to automatically interrupt the load circuit on the expiry of credit balance.
- 4.2.2.1.2 The load switch shall automatically restore the load circuit after top up.
- 4.2.2.1.3 The meter load switch shall comply with the requirements given in 2.1.
- 4.2.2.1.4 The meters shall be able to indicate absence or presence of continuous power.
- 4.2.2.1.5 The meters shall disconnect the load if power failure is detected and connect the load after normalization.
- 4.2.2.1.6 The meters shall have a programmable power limit setting that shall disconnect the load once exceeded and reconnect once the load falls below the set limit.
- 4.2.2.1.7 The MCU shall support two elements double circuit measurement. The MCU shall be equipped with 100A relay (loading switch) both in Live and Neutral circuits. These relays shall operate simultaneously. In case there is an imbalance between the Live circuit and the Neutral circuit, the MCU will take it as a tamper event and record it. The MCU will measure on the higher current without disconnecting the loading switch.
- 4.2.2.1.8 The MCU shall have a diagnostic LED to indicate the presence of communication between the MCU and the UIU.





Doc. No.	KP1/10A.2B/3/3/01
ISSUE NO.	2
REVISION NO.	3
Date of Issue	2016-06-16
Page 10 of 28	

- 4.2.2.1.9 The MCU shall continue metering and decrement credit, regardless of the state of the communications interface of the UIU.
- 4.2.2.1.10 The Live and Neutral of the MCU shall be DC immune
- 4.2.2.1.11 The MCU shall come fitted with an SCSSCAAA9 (MC171) compliant data port for programming and interrogating the meter. Two (2) sets of data interrogating and programming probes and software (1 each for optical and SCSSCAAA9 ports) shall be provided with the meter sample for evaluation. For the winning bidders, each delivery of 100,000 meters shall have 100 sets of probes and software for use with the optical and the SCSSCAAA9 ports.
- 4.2.2.1.12 The MCU shall be supplied together with a plastic card of dimension 85mm x 54 (length X height) mm and material similar to that of a credit card indicating the meter number. The meter serial number shall be engraved on the card together with its bar code version and also stored in a magnetic medium with capability of being read out when the card is swiped.
- 4.2.2.1.13 The MCU shall be with pre-loaded 3 (three) kWh.
- 4.2.2.2 User Interface Unit (UIU)
- 4.2.2.2.1 The UIU shall comply with 20-digit (STS) encryption algorithms. All correctly entered tokens shall be registered to eliminate fraud.
- 4.2.2.2.2 The UlU's keypad shall be user friendly with a LCD display for numeric credit display and language independent pictograms to identified operational features. The height of the display characters for the numeric values shall not be less than 4.5 mm.
- 4.2.2.2.3 The UIU display shall have at least seven 7-numerical characters comprising of five integers and two decimals.
- 4.2.2.2.4 The UIU shall conform to the degree of protection IP 51 as given in IEC 60529.
- 4.2.2.2.5 The UIU shall communicate with MCU through (PLC) communication link for distance not less than one hundred (100) meters.
- 4.2.2.2.6 The UIU shall be an interchangeable unit and it shall be possible to view the mated MCU on the UIU.





Doc. No.	KP1/10A.2B/3/3/01	
ISSUE NO.	2	
REVISION NO.	3	
Date of Issue	2016-06-16	
Page 11 of 28		-

- 4.2.2.2.7 The UIU shall enable loading the meter with a number of pre-purchased units of credit, without loss of any existing credit balance.
- 4.2.2.2.8 The UIU shall, upon acceptance of a valid token credit the exact amount contained on the token to the appropriate register in the meter and shall increment the register by this amount.
- 4.2.2.2.9 The UIU shall transfer the credit in kWh.
- 4.2.2.2.10 The UIU shall display the cumulative kilowatt-hour register.
- 4.2.2.2.11 The UIU shall have a means to remove digits from a partially entered number sequence-backspace key.
- 4.2.2.2.12 The UIU shall have the ability to recall the last five successful credit tokens entered and the associated dates and time.
- 4.2.2.2.13 The UIU shall be able to indicate the meter software.
- 4.2.2.2.14 The UIU shall indicate the status of the incoming supply.
- 4.2.2.2.15 The UIU shall indicate the credit status.
- 4.2.2.2.16 The UIU shall indicate token acceptance or rejection.
- 4.2.2.2.17 The UIU shall give low credit warning by means of a flag on UIU display and audio alarm. The UIU shall have option of muting the low credit warning sound by entering a code on the UIU.
- 4.2.2.2.18 The UIU keypad shall have backlight to enable keying of tokens in the dark.
- 4.2.2.2.19 The UIU shall be wall mountable
- 4.2.2.2.20 The UIU shall able to communicate with MCU when power off via 2xAA battery".



Doc. No.	KP1/10A.2B/3/3/01	
ISSUE NO.	2	
REVISION NO.	3	
Date of Issue	2016-06-16	
Page 12 of 28		

Using PLC as medium of communication between MCU and UIU

4.3 Electrical requirements

- **4.3.1** The meters shall be operated from mains with reference values of 230V, 50 Hz, with a load switching voltage range from 0.4Un to 1.3Un.
- **4.3.2** The load switch shall interrupt the supply when the voltage is below 0.4 Un and above 1.3Un.
- **4.3.3** The load switch shall automatically restore supply within a minute when the voltage falls within 0.4 1.3 Un.
- **4.3.4** The meters shall be connectable for 2-wire systems, drawing of which shall be printed on the meter body.
- 4.3.5 The meter shall have reference standard currents of:-

Ib = 5 A, Imax $\geq 80 A$

4.3.6 Power consumption:

The requirement of 2.3 applies.

4.3.7 Influence of short-time over-currents:

The requirement of 2.3 applies...

4.3.8 Influence of self-heating

The requirement of 2.3 applies.

4.3.9 Over-voltage

The requirement of 2.3 applies.

4.3.10 Insulation test

The requirement of 2.3 applies.

4.3.11 EMC test

The requirement of 2.3 applies.

Requirements 4.3.6 to 4.3.11 shall form part of the type test approval to be issued by an international or the national (of the country of manufacture) meter certifying body.

4.4 Accuracy requirements

Tests and test conditions given in 2.2 shall apply.

- **4.4.1** The meter's accuracy shall be of class 1 for active energy.
- **4.4.2** Limits of errors due to variation of the current:

The requirement of 2.3 applies.





Doc. No.	KP1/10A.2B/3/3/01	
ISSUE NO.	2	
REVISION NO.	3	
Date of Issue	2016-06-16	
Page 13 of 28		- 0

Using PLC as medium of communication between MCU and UIU

4.4.3 Limits of error due to influence quantities The requirement of 2.3 applies.

4.4.4 Test of starting and no-load condition The requirement of 2.3 applies.

4.4.5 Meter constant

The requirement of 2.3 applies.

4.4.6 Accuracy test conditions

The requirement of 2.3 applies.

Requirements of Clause 4.4 shall form part of the type test approval to be issued by an international or the national (of country of manufacture) meter certifying body.

4.5 Instructions and Marking

4.5.1 General

The requirements given in 2.1 shall apply. The information shall be in legible English, indelibly marked on the meter and of at least 4mm figure height.

4.5.2 Specific marking requirements

The following information shall be marked on each meter.

- (a) The standard transfer specification (STS) compliant serial number, in the preferred format known as a national meter number,
- (b) The STS compliance logo,
- (c) The inscription "Property of K.P. &. L. Co Ltd.",
- (d) Name or trade mark of the manufacturer;
- (e) Country of origin;
- (f) Type/model;
- (g) Meter number;
- (h) Barcode comprising of meter serial no without blank spaces;
- (i) Standard(s) to which the meter complies;





Doc. No.	KP1/10A.2B/3/3/01	
ISSUE NO.	2	
REVISION NO.	3	_
Date of Issue	2016-06-16	
Page 14 of 28		

- (j) Year of manufacture.
- 4.5.3 The following drawings and information shall be required with the tender:
 - (a) Meter drawing giving all the relevant dimensions;
 - (b) Wiring diagrams;
 - (c) Description leaflet of the meter being offered;
 - (d) Users and operational manuals.
- 4.5.4 A sample of the meter offered shall be submitted together with test tokens for; different Power Limit Settings and resets for the same, Credit and Clear Credit Tokens to aid in the testing of the meters. The manufacturer might be required to provide more tokens at no extra cost.
- 4.5.5 Copies of type approval certificate (s) with test and calibration results of the meter being offered obtained from an international or the national meter certification body shall be provided. If type approval certificate (s) is (are) from accredited meter certification laboratories (and not national or international body), then it (they) shall be accompanied with copies of certificates of accreditation, under ISO/IEC 17025 from the national or an international certification body.
- 4.5.6 The bidder shall complete clearly, all the clauses in both columns of the Schedule in Appendix B. This shall form the basis of evaluation of the submitted tender. Failure to complete this Appendix shall render the tender non-responsive. The tenderers shall indicate the details of their offer where it is different from these requirements. Where the requirement is the same, they shall indicate what is offered. Insertions such as "noted", "agreed" etc. shall be considered as non-responsive where a specific response is called for.
- 4.5.7 The supplier shall submit a Quality Assurance Plan (QAP) that will be used to ensure that the meters design, materials, workmanship, test, service capability, maintenance and documentation, will fulfill the requirements stated in the contract documents, standards, specifications and regulations.
- 4.5.8 The supplier declaration on conformity to applicable standards like ISO 9001:2008 shall be supported with copies of valid certificates. The supplier shall submit with the tender, the calibration certificates for their test equipment issued by a third party testing laboratory that is accredited to ISO/IEC 17025".





Doc. No.	KP1/10A.2B/3/3/01	
ISSUE NO.	2	
REVISION NO.	3	
Date of Issue	2016-06-16	
Page 15 of 28		

Using PLC as medium of communication between MCU and UIU

- 4.5.9 Copies of DLMS/COSEM certificates shall be submitted with this tender
- **4.5.10** The manufacturer shall produce meters that fully meet the requirements of the IEC standard, IEC 62055-51:2007 Electricity metering Payment systems Part 51: Standard transfer specifications and hence :
 - (a) Facilitates interoperability amongst hardware, software and meters supplied by other manufacturers
 - (b) Does not lock KPLC to only the bidder or any one supplier or manufacturer in its future procurement of prepayment meters, software or hardware.
 - (c) The meters shall be interoperable with the existing Smart metering Management System. The bidder shall demonstrated this before award.

5 INFORMATION AND WARRANTY (IN CASE OF TENDER AWARD)

- 5.1 Drawings and technical details shall be submitted to KPLC for approval before manufacture of the meters commences. KPLC undertakes to submit their comments or approval for the drawings within three weeks of receiving the draft copies.
- 5.2 The meter shall have a warranty against any defects, which may develop due to faulty material, calibration, transportation or workmanship for a period of eighteen months from the date of delivery. All defective meters shall be replaced at the supplier's cost.
- 5.3 KPLC shall meet the full costs of two engineers, for meter inspection and acceptance testing at the manufacturer's facility.

5.4 Samples

- 5.4.1 The tenderer shall submit one MCU and two (2) UIU samples together with the tender documents. The submitted meter samples shall be subjected to accuracy tests at KPLC's Meter Central Laboratory to verify the requirements of IEC 62053-21:2003 Clause 8.1 and to verify responsiveness to other requirements of this specification. Samples shall not be returned to the tenderers.
- 5.4.2 Bidders are advised that the Laws of Kenya require that the Kenya Bureau of Standards must approve any new meter being introduced in the country. To this end, Bidders shall furnish the Bureau with 4 (four) samples of each meter type to be supplied. Bids submitted without the meter type approval from the Bureau will NOT be considered non-





Doc. No.	KP1/10A.2B/3/3/01	
ISSUE NO.	2	
REVISION NO.	3	
Date of Issue	2016-06-16	
Page 16 of 28		

Using PLC as medium of communication between MCU and UIU

responsive. However the winning Bidder must submit this approval before the signing of the supply contract.

Bidders may communicate directly with the Kenya Bureau of Standards on this matter through the following address:

The Managing Director Kenya Bureau of Standards, P.O. Box 54974, 00200, Nairobi, Kenya.

Tel: (+254 020) 605490, 602350

Fax: (+254 020) 604031 Email: info@kebs.org

Web:http://www.kebs.org

- 5.5 The meters shall be packaged in such a manner as to minimize damage and entry of moisture during transportation and handling.
- The meters shall be packed in suitable groups and / or batches with consecutive serial numbers. Packaging shall be done only after KPLC approval
- 5.7 The meters shall be packaged in multiples of ten unless where the number of meters in a group/batch does not make a multiple of ten.
- 5.8 The number of meters packaged in a group and/or batch for handling/lifting/carrying by an operator manually shall be such that their weight does not exceed 15 kg.
- 5.9 The supplier shall indicate the delivery time versus quantities of each type of meter and his production capacity.
- 5.10 Where test and / or calibration certificates/ reports are issued by a laboratory other than the International / National Standards and Testing Authority, a copy of accreditation certificate, under ISO/IEC 17025 from the International/ National meter certification body shall be attached together with the tender documents.
- 5.11 The manufacturer shall provide current e-mail addresses, fax and telephone numbers of the national / international testing / calibration laboratories and meter certification bodies. The test certificates shall bear the product serial number of meter on offer.





Doc. No.	KP1/10A.2B/3/3/01	
ISSUE NO.	2	
REVISION NO.	3	
Date of Issue	2016-06-16	
Page 17 of 28		-

Using PLC as medium of communication between MCU and U!U

Page 17 of 28

6 ANNEXES

Annex A: Summary of Technical Data

Туре	Single phase, 2-wire, direct connected prepayment meter
Compatible networks	Single phase, 2-wire, earthed neutral
Electrical ratings	
Accuracy	kWh Class 1 (IEC 62053-21)
Voltage measurement (Un)	230V; 50Hz
Load switching voltage range	0.5 U _n to 1.3 U _n
Voltage circuit burden	2W and 10 VA
Current circuit burden	4VA @ Base reference current I _b
Current measurement	$I_b = 5 A_i^* I_{max} = 80 A.$
Protective class	Class II double insulated
MCU Enclosure	
Mounting	Rail mounting, with locking clip compatible with 35 mm DIN standard rai
Rating	IP54, suitable for installation in a pole-top or outdoor kiosk housing
Material	UV stable polycarbonate/ABS blend with flame retardant
Resistance to heat and fire	As per IEC 60695-2-1 (glow-wire)
Resistance to spread of fire	UL94-VO rated @ 1.5mm
Terminals	
Туре	Moving-cage terminal
Material	Mild steel/nickel/brass
Maximum Cable Size	10 mm²
Operating environment	
Area of application	Indoor meter
Operating temperature range	-1 °C to 60 °C
Storage temperature range	-10 °C to 60 °C
Relative humidity	Maximum 90%, annual mean 75%
Operation	
General	Credit store with decrement-on-use
Credit entry mechanism	Keypad; encrypted numeric tokens
Credit encryption method	20-digit STS
Metrological performance	
Measurement direction	Forward and reverse detection and metering





-16

Consumption indicator	Visible LED
Status indication	Visible LED
Liquid Crystal Display (LCD)	8 digits + icons; icon information, numeric information
Accurate metering range	0.05 lb to 1.2 I _{max}
Starting current	0.4% lb
Short circuit current	30 I _{max}
Disconnection Device	30 imax
Туре	Single pole latching contactor, 100 A.
Insulation; Over voltage and	Surge Protection
Insulation system classification	Protective class II
Insulation level	4 kV rms for 1 minute
Over voltage withstand	400 VAC for 48 hours
Surge immunity	
Voltage impulse withstand	SECURE n excess of 6 kV, 1.2/50 s (IEC 62052-11)
Current impulse withstand	5kA/20 s
Electromagnetic compatibility	
Electrostatic discharge	15 kV air discharge
Immunity to HF fields	80 MHz to 2 GHz @ 10V/m with load 80 MHz to 2 GHz @ 30V/m no load
Immunity to FTB	4 kV
Radio interference	Complies with requirements for CISPR 22
Specification Compliance	IEC 61000-4-2; IEC 61000-4-3; IEC 61000-4-4; IEC 61000-4-6 CISPR 22
Communication Circuitry	
Туре	PLC
	Peak Voltage 6 kV (1,2/50∃s) waveform
Rated Impulse Voltage	(According to IEC 62052-11 protective class II)
	4 kVrms (1 Minute)
Insulation properties	(According to IEC 62052-11 protective class II)
	(According to IEO 02002-11 protective class II)
Communication Distance	GDDBD metres
User Interface Unit	
Туре	PLC
Operating Range (Com)	□100 metres
	100 metres





Doc. No.	KP1/10A.2B/3/3/01
ISSUE NO.	2
REVISION NO.	3
Date of Issue	2016-06-16
Page 19 of 28	

Using PLC as medium of communication between MCU and UIU

Operating Temperature	-10 °C to 60 °C	
Storage Temperature Range		
Relative Humidity	75 %	
UIU Enclosure		
Туре	Wall mounted	
Rating	IP 51	
Material	UV stable polycarbonate/ABS blend with flame retardant	
Sealing		
Enclosure	Factory sealed, no user serviceable parts	
Туре	Language-independent	
Components	Pictographic/Numeric LCD display, keypad, LED rate of consumption	
	indicator, audio feedback	
Liquid Crystal Display (LCD)	At least 7 digits + 11 icons; icon information; numeric information display of	
Size	various meter information such as credit levels, token entry, etc	
Keypad	12-key, international standard layout including "information" and	
	"backspace" keys	
Buzzer	Feedback on key press, Token Accept and Reject melodies, low-credit	
	alarms as a factory-programmable option	
Light emitting Diode (LED)	Rate of consumption indicator (pulse rate proportional to current rate of	
	consumption)	

ANNEX B: Specifications Matrix for Split Prepayment Static Meters for active Energy - Guaranteed Technical Particulars (GTP)

CLAUSE	KPLC REQUIREMENT	MANUFACTURER'S COMPLIANCE/ REMARKS	REFERENCE PAGE IN THE SUBMITTED DOCUMENTS
4.1	Operating conditions requirements		
4.1.1	The meters shall be suitable for operation in tropical climate where temperatures may vary from -1 to + 60 degrees Celsius		
4.1.2	Average Annual Relative humidity up to 90% and altitude of up to 3,200m.		
4.1.3	The meters shall be used for measurement of active energy for domestic loads under tropical climate conditions		
4.2	Design and construction requirements		
4.2 4.2.1	General		
4.2.1.1	The requirements given in 2.1 shall apply.		





Doc. No.	KP1/10A.2B/3/3/01
ISSUE NO.	2
REVISION NO.	3
Date of Issue	2016-06-16
Page 20 of 28	

4.2.1.2 The Measurement and Control Unit (MCU) shall be of DIN rall mounting with locking clip, to fit to a 35 mm Din rall. 4.2.1.3 The MCU and UIU shall communicate via PLC for a distance of not less than one hundred (100) meters. 4.2.1.4 The meters shall be constructed as 1 phase 2-wire meters. 4.2.1.5 The meters shall have terminals as follows: The Connection to the meter shall be Bottom-In, Bottom-Out with Line in and Neutral in terminals at the base level to allow racking of the meter on a test bench. The meter terminals shall have a prediction cover against ingress of water. 4.2.1.6 The MCU dimensions shall not exceed: Height = 170 mm; Width ≈ 60 mm; and Depth ≈ 95 mm; and meter base shall be on the width side where the Din rail mount shall be located. 4.2.1.7 The MCU body shall be ultrasonically sealed for life and there should be no screws on the MCU body except for the terminal cover on the MCU body except for the terminal cover open detection. Once the terminal cover is opened, the load shall be disconnected. (a) The MCU shall be supplied with loading switch in open mode and installer can open terminal cover when MCU is not activated by commissioning code (token). (b) After installation of MCU, the installer will input a commission code (token) to close the loading switch and activate terminal cover open detection function. (c) After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will disconnect immediately of the event and decreminal cover is opened, MCU will disconnect immediately power events. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, evermin, dust, chemic	CLAUSE	KPLC REQUIREMENT	MANUFACTURER'S COMPLIANCE/ REMARKS	REFERENCE PAGE IN THE SUBMITTED DOCUMENTS
mm Din rail. 4.2.1.3 The MCU and UIU shall communicate via PLC for a distance of not less than one hundred (100) meters. 4.2.1.4 The meters shall be constructed as I phase 2-wire meters. 4.2.1.5 The meters shall have terminals as follows: The Connection to the meter shall be Bottom-In, Bottom-Out with Line in and Neutral in terminals at the base level to allow racking of the meter on a test bench. The meter terminals shall have a protection cover against ingress of water. 4.2.1.6 The MCU dimensions shall not exceed: Height = 170 mm; Width = 60 mm; and Depth = 95 mm; and meter base shall be on the width side where the Din rail mount shall be located. 4.2.1.7 The MCU body shall be ultrasonically sealed for life and there should be no screws on the MCU body except for the terminalion of cables. 4.2.1.8 The meter shall have terminal cover open detection. Once the terminal cover is opened, the load shall be disconnected. (a) The MCU shall be supplied with loading switch in open mode and installer can open terminal cover when MCU is not activated by commissioning code (token). (b) After installation of MCU, the installer will input a commission code (token) to close the loading switch and activate terminal cover open detection function. (c) After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has no power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will disconnect immediately power resumes. The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. The meters terminal loose and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance.	4.2.1.2	The Measurement and Control Unit (MCU) shall be		
### Action The MCU and UIU shall communicate via PLC for a distance of not less than one hundred (100) meters. ###################################	1	of DIN rail mounting with locking clip, to fit to a 35		1
a distance of not less than one hundred (100) metres. 4.2.1.4 The meters shall be constructed as I phase 2-wire meters. 4.2.1.5 The meters shall have terminals as follows: The Connection to the meter shall be Bottom-In, Bottom-Out with Line in and Neutral in terminals at the base level to allow racking of the meter on a test bench. The meter terminals shall have a protection cover against ingress of water. 4.2.1.6 The MCU dimensions shall not exceed: Height = 170 mm; Width = 60 mm; and Depth = 95 mm; and meter base shall be on the width side where the Din rail mount shall be located. 4.2.1.7 The MCU body shall be ultrasonically sealed for life and there should be no screws on the MCU body except for the termination of cables. 4.2.1.8 The meter shall have terminal cover open detection. Once the terminal cover is opened, the load shall be disconnected. (a) The MCU shall be supplied with loading switch in open mode and installer can open terminal cover when MCU is not activated by commissioning code (token). (b) After installation of MCU, the installer will input a commission code (token) to close the loading switch and activate terminal cover open detection function. (c) After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has no power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes. 1.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 1.3.1.10 The meters terminal holes and serves shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 1.3.1.1.11 The meters terminal holes and serves shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corros		mm Din rail.		
### 4.2.1.4 The meters shall be constructed as 1 phase 2-wire meters. #### 4.2.1.5 The meters shall have terminals as follows: The Connection to the meter shall be Bottom-In, Bottom-Out with Line in and Neutral in terminals at the base level to allow racking of the meter on a test bench. The meter terminals shall have a protection cover against ingress of water. ###################################	4.2.1.3	The MCU and UIU shall communicate via PLC for		
### ### ##############################		a distance of not less than one hundred (100) meters.		
### The meters shall have terminals as follows: The Connection to the meter shall be Bottom-In, Bottom-Out with Line in and Neutral in terminals at the base level to allow racking of the meter on a test bench. The meter terminals shall have a protection cover against ingress of water. ###################################	4.2.1,4	The meters shall be constructed as 1 phase 2-wire		
Connection to the meter shall be Bottom-In, Bottom-Out with Line in and Neutral in terminals at the base level to allow racking of the meter on a test bench. The meter terminals shall have a protection cover against ingress of water. The MCU dimensions shall not exceed: Height = 170 mm; Width = 60 mm; and Depth = 95 mm; and meter base shall be on the width side where the Din rail mount shall be located. 4.2.1.7 The MCU body shall be ultrasonically sealed for life and there should be no screws on the MCU body except for the termination of cables. 7.1.1 The MCU shall be supplied with loading switch in open mode and installer can open terminal cover when MCU is not activated by commissioning code (token). 7. After installation of MCU, the installer will input a commission code (token) to close the loading switch and activate terminal cover open detection function. 7. After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover opened disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. The meter sterminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.1.1 Terminal holes shall be of at least 10-mm diameter [meters.		
Bottom-Out with Line in and Neutral in terminals at the base level to allow racking of the meter on a test bench. The meter terminals shall have a protection cover against ingress of water. 4.2.1.6 The MCU dimensions shall not exceed: Height = 170 mm; Width = 60 mm; and Depth = 95 mm; and meter base shall be on the width side where the Din rail mount shall be located. 4.2.1.7 The MCU body shall be ultrasonically sealed for life and there should be no screws on the MCU body except for the terminal core on the MCU body except for the terminal cover open detection. Once the terminal cover is opened, the load shall be disconnected. (a) The MCU shall be supplied with loading switch in open mode and installer can open terminal cover when MCU is not activated by commissioning code (token). (b) After installation of MCU, the installer will input a commission code (token) to close the loading switch and activate terminal cover open detection function. (c) After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover opened, MCU will detect and record the event and disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. The meters terminal holes and scrows shall be of Moving-cage type made of brass or nickle-plated brass for high conductivity and corrosion resistance.	4.2.1.5	The meters shall have terminals as follows: The		
the base level to allow racking of the meter on a test bench. The meter terminals shall have a protection cover against ingress of water. 4.2.1.6 The MCU dimensions shall not exceed; Height = 170 mm; Width = 60 mm; and Depth = 95 mm; and meter base shall be on the width side where the Din rail mount shall be located. 4.2.1.7 The MCU body shall be ultrasonically sealed for life and there should be no screws on the MCU body except for the termination of cables. 4.2.1.8 The meter shall have terminal cover open detection. Once the terminal cover is opened, the load shall be disconnected. (a) The MCU shall be supplied with loading switch in open mode and installer can open terminal cover when MCU is not activated by commissioning code (token). (b) After installation of MCU, the installer will input a commission code (token) to close the loading switch and activate terminal cover open detection function. (c) After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meter sterminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance.		Connection to the meter shall be Bottom-In,		
bench. The meter terminals shall have a protection cover against ingress of water. 4.2.1.6 The MCU dimensions shall not exceed: Height = 170 mm; Width = 60 mm; and Depth = 95 mm; and meter base shall be on the width side where the Din rail mount shall be located. 4.2.1.7 The MCU body shall be ultrasonically sealed for life and there should be no screws on the MCU body except for the termination of cables. 4.2.1.8 The meter shall have terminal cover open detection. Once the terminal cover is opened, the load shall be disconnected. (a) The MCU shall be supplied with loading switch in open mode and installer can open terminal cover when MCU is not activated by commissioning code (token). (b) After installation of MCU, the installer will input a commission code (token) to close the loading switch and activate terminal cover open detection function. (c) After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance.		Bottom-Out with Line in and Neutral in terminals at		
cover against ingress of water. 1.2.1.6 The MCU dimensions shall not exceed: Height = 170 mm; Width = 60 mm; and Depth = 95 mm; and meter base shall be on the width side where the Din rail mount shall be located. 1.2.1.7 The MCU body shall be ultrasonically sealed for life and there should be no screws on the MCU body except for the termination of cables. 1.2.1.8 The meter shall have terminal cover open detection. Once the terminal cover is opened, the load shall be disconnected. (a) The MCU shall be supplied with loading switch in open mode and installer can open terminal cover when MCU is not activated by commissioning code (token). (b) After installation of MCU, the installer will input a commission code (token) to close the loading switch and activate terminal cover open detection function. (c) After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will disconnect immediately bower resumes. 1.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 1.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance.		the base level to allow racking of the meter on a test		
4.2.1.6 The MCU dimensions shall not exceed: Height = 170 mm; Width = 60 mm; and Depth = 95 mm; and meter base shall be on the width side where the Din rail mount shall be located. 4.2.1.7 The MCU body shall be ultrasonically sealed for life and there should be no screws on the MCU body except for the termination of cables. 4.2.1.8 The meter shall have terminal cover open detection. Once the terminal cover is opened, the load shall be disconnected. (a) The MCU shall be supplied with loading switch in open mode and installer can open terminal cover when MCU is not activated by commissioning code (token). (b) After installation of MCU, the installer will input a commission code (token) to close the loading switch and activate terminal cover open detection function. (c) After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter		bench. The meter terminals shall have a protection		
170 mm; Width = 60 mm; and Depth = 95 mm; and meter base shall be on the width side where the Din rail mount shall be located. 4.2.1.7 The MCU body shall be ultrasonically sealed for life and there should be no screws on the MCU body except for the termination of cables. 4.2.1.8 The meter shall have terminal cover open detection. Once the terminal cover is opened, the load shall be disconnected. (a) The MCU shall be supplied with loading switch in open mode and installer can open terminal cover when MCU is not activated by commissioning code (token). (b) After installation of MCU, the installer will input a commission code (token) to close the loading switch and activate terminal cover open detection function. (c) After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes. 4.2.1.9		cover against ingress of water.	<u></u>	
meter base shall be on the width side where the Din rail mount shall be located. 4.2.1.7 The MCU body shall be ultrasonically scaled for life and there should be no screws on the MCU body except for the terminalion of cables. The meter shall have terminal cover open detection. Once the terminal cover is opened, the load shall be disconnected. (a) The MCU shall be supplied with loading switch in open mode and installer can open terminal cover when MCU is not activated by commissioning code (token). (b) After installation of MCU, the installer will input a commission code (token) to close the loading switch and activate terminal cover open detection function. (c) After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter	4.2.1.6	The MCU dimensions shall not exceed: Height =		
rail mount shall be located. 4.2.1.7 The MCU body shall be ultrasonically sealed for life and there should be no screws on the MCU body except for the termination of cables. 4.2.1.8 The meter shall have terminal cover open detection. Once the terminal cover is opened, the load shall be disconnected. (a) The MCU shall be supplied with loading switch in open mode and installer can open terminal cover when MCU is not activated by commissioning code (token). (b) After installation of MCU, the installer will input a commission code (token) to close the loading switch and activate terminal cover open detection function. (c) After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter		170 mm; Width = 60 mm; and Depth = 95 mm; and		
4.2.1.7 The MCU body shall be ultrasonically sealed for life and there should be no screws on the MCU body except for the termination of cables. 4.2.1.8 The meter shall have terminal cover open detection. Once the terminal cover is opened, the load shall be disconnected. (a) The MCU shall be supplied with loading switch in open mode and installer can open terminal cover when MCU is not activated by commissioning code (token). (b) After installation of MCU, the installer will input a commission code (token) to close the loading switch and activate terminal cover open detection function. (c) After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter				
and there should be no screws on the MCU body except for the termination of cables. 4.2.1.8 The meter shall have terminal cover open detection. Once the terminal cover is opened, the load shall be disconnected. (a) The MCU shall be supplied with loading switch in open mode and installer can open terminal cover when MCU is not activated by commissioning code (token). (b) A fler installation of MCU, the installer will input a commission code (token) to close the loading switch and activate terminal cover open detection function. (c) After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter		rail mount shall be located.		
except for the termination of cables. The meter shall have terminal cover open detection. Once the terminal cover is opened, the load shall be disconnected. (a) The MCU shall be supplied with loading switch in open mode and installer can open terminal cover when MCU is not activated by commissioning code (token). (b) After installation of MCU, the installer will input a commission code (token) to close the loading switch and activate terminal cover open detection function. (c) After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter	4.2.1.7			
The meter shall have terminal cover open detection. Once the terminal cover is opened, the load shall be disconnected. (a) The MCU shall be supplied with loading switch in open mode and installer can open terminal cover when MCU is not activated by commissioning code (token). (b) After installation of MCU, the installer will input a commission code (token) to close the loading switch and activate terminal cover open detection function. (c) After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter				
Once the terminal cover is opened, the load shall be disconnected. (a) The MCU shall be supplied with loading switch in open mode and installer can open terminal cover when MCU is not activated by commissioning code (token). (b) After installation of MCU, the installer will input a commission code (token) to close the loading switch and activate terminal cover open detection function. (c) After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter				
disconnected. (a) The MCU shall be supplied with loading switch in open mode and installer can open terminal cover when MCU is not activated by commissioning code (token). (b) After installation of MCU, the installer will input a commission code (token) to close the loading switch and activate terminal cover open detection function. (c) After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter	4.2.1.8	I I		
(a) The MCU shall be supplied with loading switch in open mode and installer can open terminal cover when MCU is not activated by commissioning code (token). (b) After installation of MCU, the installer will input a commission code (token) to close the loading switch and activate terminal cover open detection function. (c) After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter				
open mode and installer can open terminal cover when MCU is not activated by commissioning code (token). (b) After installation of MCU, the installer will input a commission code (token) to close the loading switch and activate terminal cover open detection function. (c) After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter				
when MCU is not activated by commissioning code (token). (b) After installation of MCU, the installer will input a commission code (token) to close the loading switch and activate terminal cover open detection function. (c) After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter	(a)			
(token). (b) After installation of MCU, the installer will input a commission code (token) to close the loading switch and activate terminal cover open detection function. (c) After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter				
(b) After installation of MCU, the installer will input a commission code (token) to close the loading switch and activate terminal cover open detection function. (c) After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter	H		l i	
commission code (token) to close the loading switch and activate terminal cover open detection function. (c) After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter		8 7		
and activate terminal cover open detection function. (c) After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter	(b)			
(c) After commissioning token in put into the MCU and loading switch closes, opening of the terminal cover will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter				
loading switch closes, opening of the terminal cover will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter				
will lead to tamper. When MCU has power and terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter	(c)			
terminal cover is opened, MCU will disconnect immediately. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter				
immediately. When MCU has no power and terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter			l _M	
terminal cover is opened, MCU will detect and record the event and disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter				
record the event and disconnect immediately power resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter				
resumes. 4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter				
4.2.1.9 The MCU shall be sealed and its printed circuit boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter				
boards conformal coated in a manner so as not to allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter	4210			
allow malfunction due to ingress of moisture, vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter	7.2.1.9			
vermin, dust, chemicals and temperature extremes. 4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter				
4.2.1.10 The meters terminal holes and screws shall be of Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter			<i></i>	
Moving-cage type made of brass or nickel-plated brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter	4 2 1 10			
brass for high conductivity and corrosion resistance. 4.2.1.11 Terminal holes shall be of at least 10-mm diameter				
4.2.1.11 Terminal holes shall be of at least 10-mm diameter				
	4.2.1.11			
Harman salam and amining the management of the salam and t				
terminal holes to meter base shall not exceed 20mm.				





Doc. No.	KP1/10A.2B/3/3/01
ISSUE NO.	2
REVISION NO.	3
Date of Issue	2016-06-16
Page 21 of 28	

CLAUSE	KPLC REQUIREMENT	MANUEL OTHER DIG	Vaccination and the same
CLAUSE	APEC REGUIREMENT	MANUFACTURER'S COMPLIANCE/ REMARKS	REFERENCE PAGE IN THE SUBMITTED DOCUMENTS
4.2.1.12	The meter's terminal screw inserts shall be sealable	John Elittoei Reinartto	SCENIT LES DOCOMENTS
	with utility wire seals.		
4.2.1.13	The meters protection class shall be class II (Double		
	insulated).		40
4.2.1.14	The meters shall have a non-volatile memory		l
	capable of data storage and with long-term data		
	retention period of not less than 10 years or for the		
	certified life of the meter or whichever is greater	i	
	without an electrical supply being supplied to the	i	
	meter.		
4.2.1.15	The meters shall have register codes to indicate		
	information like instantaneous power, current credit		f l
	register, power fail counter, last credit token	ſ	
	number, value of last credit token, etc. The values		
	shall be available on the UIU display.		
4.2.1.16	The principal unit for the measured values shall be		
	the kilowatt-hour (kWh).		
4.2.1.17	The meter shall have a means of reading the credit		
	register to within a resolution of at least 0.01 kWh		
	for testing purposes.		
4.2.1.18	The meters shall detect significant reverse energy		
	(SRE) when the line and load wires are swapped.		
4.2.1.19	The meters shall continue to operate correctly and		
	decrement credit during SRE detection.		
4.2.1.20	The meters shall have LED indicators for testing		
40101	and indication of kWh consumption.		
4.2.1.21	The meters shall have an optical communication		
	port, compliant to IEC62056-21 for accessing		
	information stored inside the meter through a hand held unit.	1	1
4.2.1.22	The meters shall support two-way communication.		
4.2.1.23	The meters shall be compliant with the		
7.2.1.23	DLMS/COSEM or equivalent communication		
	protocol.		
4.2.1.24	The meters shall have PLC communication module		
	for communication to data concentrators for a		
	distance of over 1000meters.		
4.2.1.25	The meters shall work under postpaid mode or		
	prepaid mode. The switch of mode shall be done via		
	meter specific token or optical communication.		
4.2.1.26	The meters shall be supplied together with three		
ļ	copies of software for interrogating the meter data;		
İ	and it shall not be possible to reprogram the meters		
	using this software.	l l	i i
4.2.1.27	The MCU shall conform to the degree of protection		
	IP 54 as given in IEC 529. The terminals shall be so		
	designed so as to ensure protection from ingress of	JI .	
	water and dust.	il	





Doc. No.	KP1/10A.2B/3/3/01
ISSUE NO.	2
REVISION NO.	3
Date of Issue	2016-06-16
Page 22 of 28	

CLAUSE	KPLC REQUIREMENT	MANUFACTURER'S COMPLIANCE/ REMARKS	REFERENCE PAGE IN THE SUBMITTED DOCUMENTS
4.2.2	Functionality		
4.2.2.1	Measurement and Control Unit (MCU)		
4.2.2.1.1	The MCU shall have a load switch to automatically		
	interrupt the load circuit on the expiry of credit		
	balance.		
4.2.2.1.2	The load switch shall automatically restore the load		
	circuit after top up.		
4.2.2.1.3	The meter load switch shall comply with the		
	requirements given in 2.1.		
4.2.2.1.4	The meters shall be able to indicate absence or		
	presence of continuous power.		
4.2.2.1.5	The meters shall disconnect the load if power failure		22 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1
	is detected and connect the load after normalization.		
4.2.2.1.6	The meters shall have a programmable power limit		
	setting that shall disconnect the load once exceeded		
	and reconnect once the load falls below the set limit.		
4.2.2.1.7	The MCU shall support two elements double		
	circuit measurement. The MCU shall be equipped		
	with 100A relay (loading switch) both in Live and		
	Neutral circuits. These relays shall operate		
	simultaneously. In case there is an imbalance	1	
	between the Live circuit and the Neutral circuit, the		
	MCU will take it as a tamper event and record it.		l i
	The MCU will measure on the higher current		
12210	without disconnecting the loading switch.		
4.2.2.1.8	The MCU shall have a diagnostic LED to indicate		
	the presence of communication between the MCU and the UIU.		
4.2.2.1.9	The MCU shall continue metering and decrement		
4.2.2.1.9			
	credit, regardless of the state of the communications interface or the UIU.		1
4.2.2.1.10	The Live and Neutral of the MCU shall be immune		
4.2.2.1.10	to DC		
4.2.2.1.11	The MCU shall come fitted with an SCSSCAAA9		
7.2.2.1.11	(MC171) compliant data port for programming and		
	interrogating the meter. Two (2) sets of data		l I
	interrogating and programming probes and software		
	(1 each for optical and SCSSCAAA9 ports) shall be		
1	provided with the meter sample for evaluation. For		
	the winning bidders, each delivery of 100,000		1
	meters shall have 100 sets of probes and software		
	for use with the optical and the SCSSCAAA9 ports.		





Doc. No.	KP1/10A.2B/3/3/01	
ISSUE NO.	2	i.
REVISION NO.	3	
Date of Issue	2016-06-16	
Page 23 of 28		

CLAUSE	KPLC REQUIREMENT	MANUFACTURER'S	REFERENCE PAGE IN THE
		COMPLIANCE/ REMARKS	SUBMITTED DOCUMENTS
4.2.2.1.12	The MCU shall be supplied together with a plastic		
	card of dimension 85mm x 54 (length X height) mm	ľ	
	and material similar to that of a credit card		
	indicating the meter number. The meter serial		
	number shall be engraved on the card together with		
li .	its bar code version and also stored in a magnetic		
	medium with capability of being read out when the		1
100110	card is swiped.		
4.2.2.1.13	The MCU shall be with pre-loaded 3 (three) kWh.		
4.2.2.2	User Interface Unit (UIU)		
4.2.2.2.1	The UIU shall comply with 20-digit (STS)		
	encryption algorithms. All correctly entered tokens		11
1 2 2 2 2	shall be registered to eliminate fraud.		
4.2.2.2.2	The UIU's keypad shall be user friendly with a LCD		
	display for numeric credit display and language		
	independent pictograms to identified operational		
	features. The height of the display characters for the		
4.2.2.2.3	numeric values shall not be less than 4.5 mm.		
4.2.2.2.3	The UIU display shall have at least seven 7-		
i	numerical characters comprising of five integers and two decimals.		
4.2.2.2.4	The UIU shall conform to the degree of protection		- <u>-</u>
4.2.2.2.4	IP 51 as given in IEC 529.		
4.2.2.2.5	The UIU shall communicate with MCU through		-
7.2.2.2	(PLC) communication link for distance not less than		i.
	one hundred (100) meters.		
4.2.2.2.6	The UIU shall be an interchangeable unit and it shall		
1.2.2.2.0	be possible to view the mated MCU on the UIU.		
4.2.2.2.7	The UIU shall enable loading the meter with a		
	number of pre-purchased units of credit, without		
	loss of any existing credit balance.		
4.2.2.2.8	The UIU shall, upon acceptance of a valid token	-	<u> </u>
	credit the exact amount contained on the token to		
	the appropriate register in the meter and shall		
	increment the register by this amount.		
4.2.2.2.9	The UIU shall transfer the credit in kWh.		
	The UIU shall display the cumulative kilowatt-hour		
	register.		
4.2.2.2.11	The UIU shall have a means to remove digits from a		
	partially entered number sequence-backspace key.		
	The UIU shall have the ability to recall the last five		
	successful credit tokens entered and the associated		
	dates and time.		
	The UIU shall be able to indicate the meter		_ =
	software.		
	The UIU shall indicate the status of the incoming		
	supply.	<u> </u>	



Doc. No.	KP1/10A.2B/3/3/01
ISSUE NO.	2
REVISION NO.	3
Date of Issue	2016-06-16
Page 24 of 28	

CLAUSE	KPLC REQUIREMENT	MANUFACTURER'S COMPLIANCE/ REMARKS	REFERENCE PAGE IN THE SUBMITTED DOCUMENTS
4.2.2.2.15	The UIU shall indicate the credit status.		
4.2.2.2.16	The UIU shall indicate token acceptance or		
	rejection.	8	
4.2.2.2.17	The UIU shall give low credit warning by means of		
	a flag on UIU display and audio alarm. The UIU	1:	
N.	shall have option of muting the low credit warning		<u> </u>
	sound by entering a code on the UIU.		E .
4.2.2.2.18	The UIU keypad shall have backlight to enable		_
7.2.2.2.10	keying of tokens in the dark.		
4.2.2.2.19	The UIU shall be wall mountable		
			_
4.2.2.2.20	The UIU shall able to communicate with MCU		
	when power off via 2xAA battery".		
4.3	Electrical requirements		
4.3.1	The meters shall be operated from mains with		
	reference values of 230V, 50 Hz, with a load		
	switching voltage range from 0.5Un to 1.3Un.		
4.3.2	The load switch shall interrupt the supply when the		
	voltage is below 0.4 Un and above 1.3Un.		
	voltage is below 0.4 On and above 1.3On.	i	
4.3.3			
1	The load switch shall automatically restore supply		
	within a minute when the voltage falls within 0.4 –	E.	
	1.3 Un.		
4.3.4			
4.5.4	The meters shall be connectable for 2-wire systems,		
	drawing of which shall be printed on the meter		
	body.		
4.3.5		-	
4.3.3	The meter shall have reference standard currents of:-		
	$1b = 5 A, 1max \ge 80 A$		
106			
4.3.6	Power consumption:		H
	The requirement of 2.3 applies		
4.3.7	Influence of short-time over-currents:		
	The requirement of 2.3 applies.		
4.3.8	Influence of self-heating		
	The requirement of 2.3 applies.		
4.3.9			
7.5.9	Over-voltage		
	The requirement of 2.3 applies.	in the second se	
4.3.10	Insulation test		
	The requirement of 2.3 applies.		
4.3.11	EMC test		
	The requirement of 2.3 applies.		
4.4	Accuracy requirements		
··•	Tests and test conditions given in 2.2 shall apply.		
4.4.1	The meter's accuracy shall be of class 1 for active		
+.4. t	*	1	
	energy		





Doc. No.	KP1/10A.2B/3/3/01	
ISSUE NO.	2	
REVISION NO.	3	
Date of Issue	2016-06-16	
Page 25 of 28		_

CLAUSE		KPLC REQUIREMENT	MANUFACTURER'S COMPLIANCE/ REMARKS	REFERENCE PAGE IN THE SUBMITTED DOCUMENTS
4.4.2		Limits of errors due to variation of the current:		
H		The requirement of 2.3 applies.		
4.4.3		Limits of error due to influence quantities	Marie San	
		The requirement of 2.3 applies.		1
4.4.4		Test of starting and no-load condition		
		The requirement of 2.3 applies.		
4.4.5		Meter constant:		
		The requirement of 2.3 applies.		
4.4.6		Accuracy test conditions:		
		The requirement of 2.3 applies.		
4.5		Instructions and Marking	4	
4.5.1	- Ú	General		
		The requirements given in 2.1 shall apply. The		
		information shall be in legible English, indelibly	Ű.	if .
	73	marked on the meter and of at least 4mm figure		
	2/2	height.		
4.5.2		Specific marking requirements		
	- 4	The following information shall be marked on each		
	/-	meter.		
	(a)	The standard transfer specification (STS) compliant		
		serial number, in the preferred format known as a	ı	
	- 40.5	national meter number,		
		The STS compliance logo,		
		The inscription "Property of K.P. &. L. Co Ltd.",		
		Name or trade mark of the manufacturer;		
		Country of origin;		
		Type/model;		
		Meter number;		
	(h)	Barcode comprising of meter serial no without blank		
		spaces;		
		Standard(s) to which the meter complies;		
	<u>(i)</u>	Year of manufacture.		
4.5.3	-	The following drawings and information shall be		
		required with the tender:		
		Meter drawing giving all the relevant dimensions;		
		Wiring diagrams;		
		Description leaflet of the meter being offered;		
	(d)	Users and operational manuals.		
4.5.4		A sample of the meter offered shall be submitted		
		together with test tokens for; different Power Limit		
		Settings and resets for the same, Credit and Clear		1
	1	Credit Tokens to aid in the testing of the meters. The	,	
		manufacturer might be required to provide more		
	li li	tokens at no extra cost.		





Doc. No.	KP1/10A.2B/3/3/01	
ISSUE NO.	2	
REVISION NO.	3	
Date of Issue	2016-06-16	
Page 26 of 28		

CLAUSE	KPLC REQUIREMENT	MANUFACTURER'S COMPLIANCE/ REMARKS	REFERENCE PAGE IN THE SUBMITTED DOCUMENTS
4.5.5	Copies of type approval certificate (s) with test and	COMPERATOR REMARKS	SOBMITTED DOGGINEITTS
1.5.5	calibration results of the meter being offered		
	obtained from an international or the national meter		
	certification body shall be provided. If type approval	1	
	certificate (s) is (are) from accredited meter		
	certification laboratories (and not national or		
	international body), then it (they) shall be		1
ļ	accompanied with copies of certificates of		1
	accreditation, under ISO/IEC 17025 from the	1	ıl I
- 3	national or an international certification body.		
4.5.6	The bidder shall complete clearly, all the clauses in		
	both columns of the Schedule in Appendix B. This		4
	shall form the basis of evaluation of the submitted	l	1
	tender. Failure to complete this Appendix shall		
	render the tender non-responsive. The tenderers		4
	shall indicate the details of their offer where it is		4 1
	different from these requirements. Where the	(×	4 1
	requirement is the same, they shall indicate what is		4
	offered. Insertions such as "noted", "agreed" etc.		(
	shall be considered as non-responsive where a		1
	specific response is called for.		
4.5.7	The manufacturer shall provide proof of		
1	conformance to ISO 9001(2008) standards by		
	attaching valid copy certificates.		9
4.5.8	The manufacturer shall provide a list and contact	and the section of th	
	details of at least four previous utilities to which the		
	meter being offered has been supplied.		
4.5.9	The manufacturer should have supplied a minimum		
	of 200,000 pieces of the meter type offered to		4
	similar utilities in the past two years.		
4.5.10	Copies of DLMS/COSEM certificates shall be		
	submitted with this tender		
4.5.11	The manufacturer shall produce meters that fully		
	meet the requirements of the IEC standard, IEC		1
r <mark>.</mark>	62055-51:2007 - Electricity metering - Payment		1
•	systems Part 51: Standard transfer specifications and		4
_	hence:		
5	INFORMATION AND WARRANTY (IN CASE		1
	OF TENDER AWARD)		
5.1	Drawings and technical details shall be submitted to		
	KPLC for approval before manufacture of the		
	meters commences. KPLC undertakes to submit		
	their comments or approval for the drawings within		
	three weeks of receiving the draft copies.	1	1000 1 1000





Doc. No.	KP1/10A.2B/3/3/01	
ISSUE NO.	2	
REVISION NO.	3	
Date of Issue	2016-06-16	
Page 27 of 29		

CLAUSE	KPLC REQUIREMENT	MANUFACTURER'S COMPLIANCE/ REMARKS	REFERENCE PAGE IN THE SUBMITTED DOCUMENTS
5.2	The meter shall have a warranty against any defects,	RI	SOBMITTED DOCUMENTS
7.2	which may develop due to faulty material,		1
	calibration, transportation or workmanship for a		
1	period of eighteen months from the date of delivery.	ŀ	
ŀ	All defective meters shall be replaced at the		
ļ	supplier's cost.		,
5.3	KPLC shall meet the full costs of two engineers, for		
	meter inspection and acceptance testing at the		
	manufacturer's facility.		1
5.4	Samples		
5.4.1	The tenderer shall submit one MCU and two (2)		
l.	UIU samples together with the tender documents.		
	The submitted meter samples shall be subjected to	l	<u> </u>
	accuracy tests at KPLC's Meter Central Laboratory		
	to verify the requirements of IEC 62053-21:2003		
	Clause 8.1 and to verify responsiveness to other	Ī	
	requirements of this specification. Samples shall not		
	be returned to the tenderers.		
5.4.2	Bidders may communicate directly with the Kenya		
_	Bureau of Standards on this matter through the		
	following address:		
		1	
	The Managing Director		
	Kenya Bureau of Standards,		
	P.O. Box 54974, 00200,		
	Nairobi, Kenya.		
	Tel: (+254 020) 605490, 602350		
	Fax: (+254 020) 604031 Email: info@kebs.org		
	Web:http://www.kebs.org		
5.5	The meters shall be packaged in such a manner as to		·
	minimize damage and entry of moisture during		1
	transportation and handling.		
5.6	The meters shall be packed in suitable groups and /		
	or batches with consecutive serial numbers.		
	Packaging shall be done only after KPLC approval		4
5.7	The meters shall be packaged in multiples of ten		
	unless where the number of meters in a group/batch		
	does not make a multiple of ten.		1
5.8	The number of meters packaged in a group and/or		
	batch for handling/lifting/carrying by an operator		(
	manually shall be such that their weight does not		1
	exceed 15 kg.		
5.9	The supplier shall indicate the delivery time versus		
	quantities of each type of meter and his production		1 1
	capacity.		1





Doc. No.	KP1/10A.2B/3/3/01	
ISSUE NO.	2	
REVISION NO.	3	
Date of Issue	2016-06-16	
Page 28 of 28	2010-00-10	

CLAUSE	KPLC REQUIREMENT	MANUFACTURER'S COMPLIANCE/ REMARKS	REFERENCE PAGE IN THE SUBMITTED DOCUMENTS
5.10	Where test and / or calibration certificates/ reports are issued by a laboratory other than the International / National Standards and Testing Authority, a copy of accreditation certificate, under ISO/IEC 17025 from the International/ National meter certification body shall be attached together with the tender documents.		
11.5	The manufacturer shall provide current e-mail addresses, fax and telephone numbers of the national / international testing / calibration laboratories and meter certification bodies. The test certificates shall bear the product serial number of meter on offer.		

Manufacturer's	Declaration:	l on	behalf	of
***************************************	• • • • • • • • • • • • • • • • • • • •	declare that the above specifications matrix c	onforms	to
a typical tender meter, type being offered for this tende				
Signature & Sta	mp			

